



常用晶体管参数列表-P、Sxxx系列

Version:1.0

TYPE	SPECIFICATION	TYPE	SPECIFICATION
	Pxxx系列		
P6N60	N-FET 600V 6A 125W 1W8	SS8050	SI-N 40V 1.5A 1W 100MHz
PH2222A	SI-N 75V 0.8A 0.5W PLASTI	SS8550	SI-P 40V 1.5A 1W 100MHz
PH2369	SI-N 15V 0.5A 0.5W 12/18ns	SSM2210P	2xSI-N 40V 20mA 0.5W 200MHz
PN2222A	SI-N 75V 0.8A 0.5W PLASTI	SSM2220P	2xSI-P 36V 20mA 0.5W 190MHz
PN2907	SI-P 40V 0.6A 0.4W PLASTI	STA301A	N-ARRAY 3x60V 4A B>1K
PN2907A	SI-P 60V 0.6A 0.4W PLASTI	STA341M	P/N-ARRAY 30V 1A B>100
PN3563	SI-N 30V 50mA 0.2W 600MHz	STA401A	N-ARRAY 4x60V 4A B>1K
PN3638	SI-P 25V 0.5A 0.625W 100MHz	STA402A	P-ARRAY 4x50V 4A B>1K
R1004	SI-N 50V 0.1A 47K/47	STA403	N-ARRAY 4x100V 4A B>1K
RFP40N10	N-FET 100V 40A 160W 0.04E	STA434A	P/N-ARRAY 2x60V 4A 20W B>
	Sxxx系列	STA441C	N-ARRAY 4x160V 1.5A B>40
S175	RF PWR AMP TRANSISTOR	STA451C	P/N-ARRAY 2x60V 3A b>40
S1854	DRIVER STAGE 112.5/117.5V	STA4371A	N-ARRAY 4x60V 2A B>2K
S2000AF	SI-N 1500V 8A 50W 0.7us	STA8012	TRANSISTOR ARRAY
S2000N	SI-N 1500V 8A 50W 0.7us	STA901M	TRANSISTOR ARRAY
S2055N	SI-N+D 1500V 8A 50W 0.3us	STP3NA60	N-FET 600V 2.9A 80W <4E
S2530A	SI-N 1000V 10A 100W	STP3NA60F	N-FET 600V 2.1A 40W <4E
S9011	SI-N 40V 0.5A 625mW	STP4NA60	N-FET 600V 4.3A 100W <2E2
S9012	SI-P 40V 0.5A 625mW 150MHz	STP4NA60F	N-FET 600V 2.7A 40W <2E2
S9013	SI-N 40V 0.5A 625mW 150MHz	STP4NA80	N-FET 600V 4A 110W <3E
S9014	SI-N 45V 0.5A 625mW 150MHz	STP4NA80F	N-FET 800V 2.5A 45W <3E
S9015	SI-P 40V 0.5A 625mW 150MHz	STW15NA50	N-FET 500V 14.6A 190W
S9016	SI-N 40V 0.5A 625mW 600MHz	SUP70N06-14	N-FET 60V 70A 142W 0.014E
S9018	SI-N 40V 0.5A 625mW 600MHz		
S8050	SI-N 20V 1W 0.7A 100MHz		
S8550	SI-P 20V 1W 0.7A 100MHz		
SGSF313	SI-N 450V 7A 70W 0.3us		
SGSF313XI	SI-N 1000V 5A 25W 0.3us		
SGSF344	SI-N 600V 7A 85W		
SGSF445	SI-N 600V 7A 95W		
SGSF464	SI-N 600V 10A 140W		
SGSIF344	SI-N 600V 7A 35W		
SGSIF444	SI-N 600V 7A 55W		
SLA4061	N-DARL 120V 5A 25W POWER		
SLA4390	DARLINGTON ARRAY		