



常用晶体管参数列表-2Nxxxx系列

Version:1.0

TYPE	SPECIFICATION	TYPE	SPECIFICATION
2N109	GE-P 0.15A 0.165W	2N5090	SI-N 55V 0.4A 4W 5mA
2N1304	GE-N 25V 0.3A 0.15W 10MHz	2N5109	SI-N 40V 0.5A 2.5W 1.5GHz
2N1305	GE-P 30V 0.3A 0.15W 5MHz	2N5116	P-FET 30V 5mA 150E Up<4V
2N1307	GE-P 30V 0.3A 0.15W B>60	2N5154	SI-N 100V 2A 10W
2N1613	SI-N 75V 1A 0.8W 60MHz	2N5179	SI-N 20V 50mA 0.2W>1GHz
2N1711	SI-N 75V 1A 0.8W 70MHz	2N5192	SI-N 80V 4A 40W 2MHz
2N1893	SI-N120V 0.5A 0.8W	2N5240	SI-N 375V 5A 100W>2MHz
2N2102	SI-N 120V 1A 1W<120MHz	2N5298	SI-N 80V 4A 36W>0.8MHz
2N2148	GE-P 60V 5A 12.5W	2N5308	N-DARL 40V 0.3A 0.4W B>7K
2N2165	SI-P 30V 50mA 0.15W 18MHz	2N5320	SI-N 100V 2A 10W AFSWITCH
2N2166	SI-P 15V 50mA 0.15W 10MHz	2N5322	SI-P 100V 2A 10W AFSWITCH
2N2219A	SI-N 40V 0.8A 0.8W 250MHz	2N5401	SI-P 160V 0.6A 0.31W
2N2222A	SI-N 40V 0.8A 0.5W 300MHz	2N5416	SI-P 350V 1A 10W 150MHz
2N2223	2xSI-N 100V 0.5A 0.6W>50	2N543	N-FET 25V 0.4A 0.3W 7E
2N2223A	2xSI-N 100V 0.5A 0.6W>50	2N5457	N-FET 25V 1mA Up<6V
2N2243A	SI-N 120V 1A 0.8W 50MHz	2N5458	N-FET 25V 2.9mA UNI
2N2369A	SI-N 40V 0.2A 0.36W 12/18ns	2N5460	P-FET 40V 5mA Up<GEN. P
2N2857	SI-N 30V 40mA 0.2W>1GHz	2N5461	P-FET 40V 9mA 0.31W
2N2894	SI-P 12V 0.2A 1.2W 60/90ns	2N5485	P-FET 25V 4mA Up<4A
2N2905A	SI-P 60V 0.6A 0.6W 45/100	2N5551	SI-N 180V 0.6A 0.31W VID
2N2906A	SI-P 60V 0.6A 0.4W 45/100	2N5589	SI-N 36V 0.6A 3W 175MHz
2N2907A	SI-P 60V 0.6A 0.4W 45/100	2N5639	N-FET 30V 10mA 310mW
2N2917	SI-N 45V 0.03A>60Mz	2N5672	SI-N 150V 30A 140W 0.5us
2N2926	SI-N 25V 0.1A 0.2W 300MHz	2N5680	SI-P 120V 1A 1W
2N2955	GE-P 40V 0.1A 0.15W 200MHz	2N5682	SI-N 120V 1A 1W>30MHz
2N3019	SI-N 140V 1A 0.8W 100MHz	2N5684	SI-P 80V 50A 200W
2N3053	SI-N 60V 0.7A 5W 100MHz	2N5686	SI-N 80V 50A 300W>2MHz
2N3054	SI-N 90V 4A 25W 3MHz	2N5770	SI-N 30V 0.05A 0.7W>900MHz
2N3055	SI-N 100V 15A 115W 800MHz	2N5771	SI-P 15V 50mA 625W>850MHz
2N3055	SI-N 100V 15A 115W 800MHz	2N5876	SI-P 80V 10A 150>4MHz
2N3055H	SI-N 100V 15A 115W 800MHz	2N5878	SI-N 80V 10A 150W>4MHz
2N3251	SI-P 50V 0.2A 0.36W	2N5879	SI-N 60V 10A 150>4MHz
2N3375	SI-N 40V 0.5A 11.6W 500MHz	2N5884	SI-P 80V 25A 200W AFPOWSW
2N3439	SI-N 450V 1A 10W 15MHz	2N5886	SI-N 80V 25A 200W>4MHz
2N3440	SI-N 300V 1A 10W 15MHz	2N6031	SI-P 140V 16A 200W 1MHz
2N3441	SI-N 160V 3A 25W POWER	2N6050	P-DRL+D 60V 12A 100W
2N3442	SI-N 160V 10A 117W 0.8MHz	2N6059	SI-N 100V 12A 150W
2N3495	SI-P 120V 0.1A 0.6W>150MHz	2N6083	SI-N 36V 5A PQ=30W 175MHz
2N3502	SI-P 45V 0.6A 0.7W 200MHz	2N6098	SI-N 70V 10A 75W AFPOWSWTH
2N3553	SI-N 65V 0.35A 7W 500MHz	2N6099	SI-N 70V 10A 75W AFPOWSWTH

TYPE	SPECIFICATION	TYPE	SPECIFICATION
2N3571	SI-N 30V 0.05A 0.2W 1.4GHz	2N4391	N-FET 40V 50mA 30E Up<10V
2N3583	SI-N 250/175V 2A 35W>10MHz	2N4392	N-FET 40V 25mA 60E Up<5V
2N3632	SI-N 40V 0.25A 23W 400MHz	2N4393	N-FET 40V 5mA 100E Up<3V
2N3646	SI-N 40V 0.2A 0.2W	2N4401	SI-N 60V 0.6A 200MHz
2N3700	SI-N 140V 1A 0.5W 200MHz	2N4403	SI-P 40V 0.6A 200MHz
2N3707	SI-N 30V 0.03A 0.36W 100MHz	2N4416	N-FET 30V 15mA VHF/UHF
2N3708	SI-N 30V 0.03A 0.36W 80MHz	2N4420	SI-N 40V 0.2A 0.36W 12/18ns
2N3716	SI-N 100V 10A 150W 4MHz	2N4427	SI-N 40V 0.4A 1W 175MHz
2N3725	SI-N 80V 0.5A 1A 35/60ns	2N4906	SI-P 80V 5A 87.5W>4MHz
2N3740	SI-P 60V 4A 25W 4MHz	2N4920	SI-P 80V 1A 30W
2N3741	SI-N 80V 4A 25W 4MHz	2N4923	SI-N 80V 1A 30W
2N3742	SI-N 300V 0.05A 1W>30MHz	2N5038	SI-N 150V 20A 140W 0.5us
2N3767	SI-N 100V 4A 20W 10MHz	2N6109	SI-P 60V 7A 40W 10MHz
2N3771	SI-N 50V 30A 150W POWER	2N6124	SI-P 45V 4A 40W
2N3772	SI-N 100V 20A 150W POWER	2N6211	SI-P 275V 2A 20W 20MHz
2N3773	SI-N 160V 16A 150W POWER	2N6213	SI-P 400V 2A 35W>20MHz
2N3792	SI-P 80V 10A 150W 4MHz	2N6248	SI-P 110V 15A 125W>6MHz
2N3819	N-FET 25V 20mA 0.36W	2N6284	N-DARL 100V 20A 150W B>75
2N3820	P-FET 20V 15mA 0.36W	2N6356	N-DARL 50V 20A 150W B>150
2N3821	N-FET 50V 2.5mA 0.3W	2N6422	SI-P 500V 2A 35W>10MHz
2N3824	N-FET 50V 10mA 0.3W<250E	2N6427	N-DARL 40V 0.5A 0.625W
2N3866	SI-N 55V 0.4A 1W 175Mz	2N6476	SI-P 130V 4A 16W 5MHz
2N3904	SI-N 60V 0.2A 0.35W 300MHz	2N6488	SI-N 90V 15A 75W
2N3906	SI-P 40V 0.2A 0.35W 250MHz	2N6491	SI-P 90V 15A 30W
2N3909	P-FET 20V 10mA 0.3W	2N6517	SI-N 350V 0.5A 0.625W>40
2N3958	N-FET 50V 5mA 0.25W	2N6520	SI-P 350V 0.5A 0.625W>40
2N3963	SI-P 80V 0.2A 0.36>40MHz	2N6547	SI-N 850/400V 15A 175W
2N3972	N-FET 40V 50mA 1.8W	2N6556	SI-P 100V 1A 10W>75MHz
2N4001	SI-N 100V 1A 15W 40MHz	2N6609	SI-P 160V 16A 150W 2MHz
2N4033	SI-P 80V 1A 0.8W 150MHz	2N6660	N-FET 60V 2A 6.25W 3E
2N4036	SI-P 90V 1A 1W 60MHz	2N6661	N-FET 90V 2A 6.2W 4E
2N409	GE-P 13V 15mA 80mW 6.8MHz	2N6675	SI-N 400V 15A
2N4126	SI-P 80V 200mA HF	2N6678	SI-N 400V 15A
2N4220	N-FET 30V 0.2A	2N6716	SI-N 60V 2A 2W 50MHz
2N4236	SI-P 80V 3A 1W>3MHz	2N6718	SI-N 100V 2A 2W 50MHz
2N427	GE-P 30V 0.4A 0.15W B>40	2N6725	N-DARL 60V 2A 1W B>15K
2N428	GE-P 30V 0.4A 0.15W B>60	2N6728	SI-P 60V 2A 2W>50MHz
2N4286	SI-N 30V 0.05A 0.25W	2N697	SI-N 60V 1A 0.6V<50MHz
2N4287	SI-N 45V 0.1A 0.25W 40MHz	2N7002	N-FET 60V 0.115A 0.2W 7E5
2N4291	SI-P 40V 0.2A 0.25W 150MHz	2N914	SI-N 40V 0.5A<40/40NS SW
2N4302	N-FET 30V 0.5mA 0.3W	2N918	SI-N 30V 50mA 0.2W 600MHz
2N4347	SI-N 140V 5A 100W 0.8MHz		
2N4348	SI-N 140V 10A 120W>0.2MHz		
2N4351	N-FET 30V 30mA 0.3W 140MHz		