



## 常用晶体管参数列表-2SBxxx系列

Version:1.0

TYPE	SPECIFICATION	TYPE	SPECIFICATION
2SB1009	SI-P 40V 2A 10W 100MHz	2SB524	SI-P 60V 1.5A 10W 70MHz
2SB1010	SI-P 40V 2A 0.75W 100MHz	2SB527	SI-P 110V 0.8A 10W 70MHz
2SB1012K	P-DARL 120V 1.5A 8W	2SB531	SI-P 90V 6A 50W 8MHz
2SB1013	SI-P 20V 2A 0.7W	2SB536	SI-P 130V 1.5A 20W 40MHz
2SB1015	SI-P 60V 3A 25W 0.4us	2SB537	SI-P 130V 1.5A 20W 60MHz
2SB1016	SI-P 100V 5A 30W 5MHz	2SB541	SI-P 110V 8A 80W 9MHz
2SB1017	SI-P 80V 4A 25W 9MHz	2SB544	SI-P 25V 1A 0.9W 180MHz
2SB1018	SI-P 100V 7A 30W 0.4us	2SB546A	SI-P 200V 2A 25W 5MHz
2SB1020	P-DARL+D 100V 7A 30W 0.8us	2SB549	SI-P 120V 0.8A 10W 80MHz
2SB1023	P-DARL+D 60V 3A 20W B=5K	2SB557	SI-P 120V 8A 80W
2SB1035	SI-P 30V 1A 0.9W 100MHz	2SB560	SI-P 100V 0.7A 0.9W 100MHz
2SB1039	SI-P 100V 4A 40W 20MHz	2SB561	SI-P 25V 0.7A 0.5W
2SB1050	SI-P 30V 5A 1W 120MHz	2SB564	SI-P 30V 1A 0.8W
2SB1055	SI-P 120V 6A 70W 20MHz	2SB598	SI-P 25V 1A 0.5W 180MHz
2SB1065	SI-P 60V 3A 10W	2SB600	SI-P 200V 15A 200W 4MHz
2SB1066	SI-P 50V 3A 1W 70MHz	2SB601	P-DARK 100V 5A 30W
2SB1068	SI-P 20V 2A 0.75W 180MHz	2SB605	SI-P 60V 0.7A 0.8W 120MHz
2SB1071	SI-P 40V 4A 25W 150MHz	2SB621	SI-N 25V 1.5A 0.6W 200MHz
2SB1077	P-DARL 60V 4A 40W>1K	2SB621A	SI-N 50V 1A 0.75W 200MHz
2SB1086	SI-P 160V 1.5A 20W 50MHz	2SB631	SI-P 100V 1A 8W
2SB1098	P-DARL+D 100V 5A 20W B=80	2SB632	SI-P 25V 2A 10W 100MHz
2SB1099	P-DARL+D 100V 8A 25W B=6K	2SB633	SI-P 100V 6A 40W 15MHz
2SB1100	P-DARL+D 100V 10A 30W B=6	2SB637	SI-P 50V 0.1A 0.3W 200MHz
2SB1109	SI-P 160V 0.1A 1.25W	2SB641	SI-P 30V 0.1A 120MHz
2SB1109S	SI-P 160V 0.1A 1.25W	2SB647	SI-P 120V 1A 0.9W 140MHz
2SB1117	SI-P 30V 3A 1W 280MHz	2SB649A	SI-P 160V 1.5A 1W 140MHz
2SB1120	SI-P 20V 2.5A 0.5W 250MHz	2SB656	SI-P 160V 12A 125W 20MHz
2SB1121T	SI-P 30V 2A 150MHz	2SB673	P-DARL+D 100V 7A 40W 0.8us
2SB1123	SI-P 60V 2A 0.5W 150MHz	2SB676	P-DARL 100V 4A 30W 0.15us
2SB1132	SI-P 40V 1A 0.5W 150MHz	2SB681	SI-N 150V 12A 100W 13MHz
2SB1133	SI-P 60V 3A 25W 40MHz	2SB688	SI-P 120V 8A 80W 10MHz
2SB1134	SI-P 60V 5A 25W 30MHz	2SB700	SI-P 160V 12A 100W
2SB1140	SI-P 25V 5A 10W 320MHz	2SB703	SI-P 100V 4A 40W 18MHz
2SB1141	SI-P 20V 1.2A 10W 150MHz	2SB705	SI-P 140V 10A 120W 17MHz
2SB1143	SI-P 60V 4A 10W 140MHz	2SB707	SI-P 80V 7A 40W POWER
2SB1146	P-DARL 120V 6A 25W	2SB709	SI-P 45V 0.1A 0.2W 80MHz
2SB1149	P-DARL 100V 3A 15W B=10K	2SB716	SI-P 120V 0.05A 0.75W
2SB1151	SI-P 60V 5A 20W	2SB720	SI-P 200V 2A 25W 100MHz
2SB1154	SI-P 130V 10A 70W 30MHz	2SB727	P-DARL+D 120V 6A 50W>1K
2SB1156	SI-P 130V 20A 100W	2SB731	SI-P 60V 1A 10W 75MHz

TYPE	SPECIFICATION	TYPE	SPECIFICATION
2SB1162	SI-P 160V 12A 120W	2SB733	SI-P 20V 2A 1W>50MHz
2SB1163	SI-P 170V 15A 150W	2SB734	SI-P 60V 1A 1W 80MHz
2SB1166	SI-P 60V 8A 20W 130MHz	2SB739	SI-P 20/16V 2A 0.9W 80MHz
2SB1168	SI-P 120V 4A 20W 130MHz	2SB740	SI-P 70V 1A 0.9W
2SB1182	SI-P 40V 2A 10W 100MHz	2SB744	SI-P 70V 3A 10W 45MHz
2SB1184	SI-P 60V 3A 15W 70MHz	2SB750	P-DARL+D 60V 2A 35W B>100
2SB1185	SI-P 50V 3A 25W 70MHz	2SB753	SI-P 100V 7A 40W 0.4us
2SB1186	SI-P 120V 1.5A 20W 50MHz	2SB764	SI-P 60V 1A 0.9W 150MHz
2SB1187	SI-P 80V 3A 35W	2SB765	P-DARL+D 120V 3A 30W B>1K
2SB1188	SI-P 40V 2A 100MHz	2SB766	SI-P 30V 1A 200MHz
2SB1202	SI-P 60V 3A 15W 150MHz	2SB772	SI-P 40V 3A 10W 80MHz
2SB1203	SI-P 60V 5A 20W 130MHz	2SB774	SI-P 30V 0.1A 0.4W 150MHz
2SB1204	SI-P 60V 8A 20W 130MHz	2SB775	SI-P 100V 6A 60W 13MHz
2SB1205	SI-P 25V 5A 10W 320MHz	2SB776	SI-P 120V 7A 70W 15MHz
2SB1212	SI-P 160V 1.5A 0.9W 50MHz	2SB788	SI-P 120V 0.02A 0.4W 150MHz
2SB1223	P-DARL+D 70V 4A 20W 20MHz	2SB791	P-DARL+D 120V 8A 40W B>10
2SB1236	SI-P 120V 1.5A 1W 50MHz	2SB794	P-DARL+D 60V 1.5A 10W B=7
2SB1237	SI-P 40V 1A 1W 150MHz	2SB795	P-DARL+D 80V 1.5A 10W B<3
2SB1238	SI-P 80V 0.7A 1W 100MHz	2SB808	SI-P 20V 0.7A 0.25W 250MHz
2SB1240	SI-P 40V 2A 1W 100MHz	2SB810	SI-P 30V 0.7A 0.35W 160MHz
2SB1243	SI-P 60V 3A 1W	2SB815	SI-P 20V 0.7A 0.25W 250MHz
2SB1254	P-DARL 160V 7A 70W	2SB816	SI-P 150V 8A 80W 15MHz
2SB1255	P-DARL 160V 8A 100W B=5K	2SB817	SI-P 160V 12A 100W
2SB1258	P-DARL+D 100V 6A 30W B=1K	2SB817F	SI-P 160V 12A 90W 15MHz
2SB1274	SI-P 60V 3A 30W 100MHz	2SB819	SI-P 50V 1.5A 1W 150MHz
2SB1282	P-DARL+D 100V 4A 25W 50MHz	2SB822	SI-P 40V 2A 0.75W 100MHz
2SB1292	SI-P 80V 5A 30W	2SB824	SI-P 60V 5A 30W 30MHz
2SB1302	SI-P 25V 5A 320MHz	2SB825	SI-P 60V 7A 40W 10MHz
2SB1318	P-DARL+D 100V 3A 1W B>200	2SB826	SI-P 60V 12A 40W 10MHz
2SB1326	SI-P 30V 5A 0.3W 120MHz	2SB827	SI-P 60V 7A 80W 10MHz
2SB1329	SI-P 40V 1A 1.2W 150MHz	2SB828	SI-P 60V 12A 80W 10MHz
2SB1330	SI-P 120V 0.7A 1.2W 100MHz	2SB829	SI-P 60V 15A 90W 20MHz
2SB1331	SI-P 32V 2A 1.2W 100MHz	2SB857	SI-P 50V 4A 40W NF/S-L
2SB1353E	SI-P 120V 1.5A 1.8W 50MHz	2SB861	SI-P 200V 2A 30W
2SB1361	SI-P 150V 9A 100W 15MHz	2SB863	SI-P 140V 10A 100W 15MHz
2SB1370	SI-P 60V 3A 30W 15MHz	2SB865	P-DARL 80V 1.5A 0.9W
2SB1373	SI-P 160V 12A 2.5W 15MHz	2SB873	SI-P 30V 5A 1W 120MHz
2SB1375	SI-P 60V 3A 25W 9MHz	2SB882	P-DARL+D 70V 10A 40W B>5K
2SB1382	P-DARL+D 120V 16A 75W B>2	2SB883	P-DARL+D 70V 15A 70W B=5K
2SB1393	SI-P 30V 3A 2W 30MHz	2SB884	P-DARK+D 110V 3A 30W B=4K
2SB1240	SI-P 120V 16A 80W 50MHz	2SB885	P-DARL+D 110V 3A 35W B=4K
2SB1425	SI-P 20V 2A 1W 90MHz	2SB891	SI-P 40V 2A 5W 100MHz
2SB1429	SI-P 180V 15A 150W 10MHz	2SB892	SI-P 60V 2A 1W
2SB1434	SI-P 50V 2A 1W 110MHz	2SB895A	P-DARL+D 60V 1A B=8000
2SB1468	SI-P 60/30V 12A 25W	2SB897	P-DARL+D 100V 10A 80W B>1
2SB1470	P-DARL 160V 8A 150W B>5K	2SB908	P-DARL+D 80V 4A 15W 0.15us

TYPE	SPECIFICATION	TYPE	SPECIFICATION
2SB1490	P-DARL 160V 7A 90W B>5K	2SB909	SI-P 40V 1A 1W 150MHz
2SB1493	P-DARL 160/140V 7A 70W B>20	2SB922	SI-P 120V 12A 80W 20MHz
2SB1503	P-DARL 160V 8A 120W B>5K	2SB926	SI-P 30V 2A 0.75W
2SB1556	P-DARL 140V 8A 120W B>5K	2SB938A	P-DARL+D 60V 4A 40W B>1K
2SB1557	P-DARL 140V 7A 100W B>5K	2SB940	SI-P 200V 2A 35W 30MHz
2SB1559	P-DARL 160V 8A 80W B>5K	2SB941	SI-P 60V 3A 35W POWER
2SB1560	P-DARL 160V 10A 100W 50MHz	2SB945	SI-P 130V 5A 40W 30MHz
2SB1565	SI-P 80V 3A 25W 15MHz	2SB946	SI-P 130V 7A 40W 30MHz
2SB1587	P-DARL+D 160V 8A 70W B>5K	2SB950A	P-DARL+D 80V 4A 40W B>1K
2SB1624	P-DARL 110V 6A 60W B>5K	2SB953A	SI-P 50V 7A 30W 105MHz
2SB206	GE-P 80V 30A 80W	2SB955	P-DARL+D 120V 10A 50W B=4
2SB325	GE-P 32V 1A 0.25W	2SB975	P-DARL+D 110V 8A 40W B>6K
2SB337	GE-P 50V 7A 30W LF-POWER	2SB976	SI-P 27V 5A 0.75W 120MHz
2SB407	GE-P 30V 7A 30W	2SB985	SI-P 60V 3A 1W 150MHz
2SB2481	GE-P 32V 1A 6W 15KHz	2SB986	SI-P 60V 4A 10W 150MHz
2SB492	GE-P 25V 2A 6W	2SB988	SI-P 60V 3A 30W<400/2200
2SB511E	SI-P 35V 1.5A 10W 8MHz		