



常用晶体管参数列表-Axxxx系列

Version:1.0

TYPE	SPECIFICATION	TYPE	SPECIFICATION
AC121	GE-P 20V 0.3A 0.9W	AF106	GE-P 25V 10mA 220MHz VHF
AC122	GE-P 30V 0.2A 0.225W	AF109R	GE-P 20V 12mA 260MHz VHF
AC125	GE-P 32V 0.2A	AF118	GE-P 70V 30mA 375mW 125MHz
AC126	GE-P 32V 0.2A 0.5W	AF121	GE-P 25V 10mA 270MHz
AC127	GE-N 32V 0.5A	AF125	GE-P 32V 10mA 75MHz
AC128	GE-P 32V 1A 1W	AF127	GE-P 32V 10mA 75MHz
AC128/176K	GE N/P PAIRED . COOLED	AF139	GE-P 20V 10mA 550MHz
AC128K	GE-P 32V 1A 1W	AF200	GE-P 25V 10mA 0.145MHz
AC131	GE-P 30V 1A 0.75W	AF201	GE-P 25V 10mA 0.145MHz
AC132	GE-P 32V 0.2A 0.5W	AF239S	GE-P 15V 10mA 700MHz
AC138	GE-P 32V 1.2A 0.22W 1.5MHz	AF279	GE-P 15V 10mA 60mW 780MHz
AC141K	GE-N 32V 1.2A 1W	AF279S	GE-P 20V 10mA 0.6W
AC151	GE-P 32V 0.2A 0.9W	AF280	GE-P UHF MIXER 550MHz
AC153	GE-P 32V 2A 1W	AF306	GE-P 25V 15mA 60mW 500MHz
AC153K	GE-P 32V 2A 1W	AF367	GE-P 153V 10mA UHF 800MHz
AC176K	GE-N 32V 1A 1W	AF379	GE-P UHF 1250MHz
AC180	GE-P 32V 1.5A 0.3W 1MHz		
AC187	GE-N 25V 1A 1W		
AC187/188K	GE-P PA/RED. COOLED		
AC187K	GE-N 25V 1A 1W COOLED		
AC188	GE-P 25V 1A 1W		
AC188K	GE-P 25V 1A 1W		
AD133	GE-P 50V 15A 36W	AL102	GE-P 130V 6A 30W
AD136	GE-P 40V 10A 11W	AL112	GE-P 130V 6A 30W
AD139	GE-P 32V 3.5A 13W	ASY27	GE-P 25V 0.2A 0.15W
AD148	GE-P 32V 3.5A 13.5W	ASY77	GE-P 60V 1A 0.26W 500MHz
AD149	GE-P 50V 3.5A 27W	ASZ15	GE-P 100V 8A 30W
AD161	GE-N 32V 1A 6W	ASZ18	GE-P 100V 8A 30W
AD161/162	GE N/P 32V 1A 6W PA/RED		
AD162	GE-P 32V 1A 6W		
AD165	GE-N 25V 1A 6W		
AD166	GE-P 60V 5A 27.5W		